

??? ????????????? ?????

???? ??????? 113,00 €

??????????

- ??????????

The CDE-201R is an affordable single-DIN solution that steps up your sound to Alpine quality and offers many connectivity features to keep you entertained on the road.

Connect your Android phone to enjoy all your stored audio content, stream Spotify or internet radio, or simply connect a USB stick - there are many connectivity solutions possible with this Alpine head unit.

Wireless remote controls are available as accessory.

???????????????? & ??????????????

Features

Tuner

- Memory Presets: Preset Stations (FM:18, MW:6, LW:6)
- Memory: Auto Memory

RDS

- RDS Functions: AF, TA, TP, PTY, EON
- PTY (Programme Type) Display

Disc Player

- Disc Type: CD Player
- Disc Playback Type: CD, CD-R/RW
- Music Playback: CDDA, MP3, WMA Playback
- M.I.X. Random Play
- Repeat: Track, All
- Playback Control: Play/Pause/Forward/Backward
- CD Text Display
- CD Text Name Search
- 24-bit DAC
- Zero data Mute

USB Media Connection

- Front USB Connection
- MP3, WMA, FLAC Playback
- Folder Up/Down
- M.I.X. Random Play
- Repeat: Track, Album, All

- USB AOA (Android Open Accessory) 2.0

Sound Tuning

- Subwoofer Level Adjustment
- BASS ENGINE SQ: Level Control 0-6
- Subwoofer Phase Select: 0°/180°
- Subwoofer System Select
- High Pass Filter
- Low Pass Filter
- 2V Voltage 2PreOuts
- 10 Equalizer PreSets: Flat, Pops, Rock, News, Jazz, Electrical Dance, Hip Hop, Easy Listening, Country and Classical
- 3-band Parametric Equalizer

General

- Power Output: 4 x 50 W High Power Amplifier
- Display LCD: 14 Segments White LCD Display 1Line
- Control Type: Rotary Encoder Knob
- Green/Red Selectable Illumination Buttons
- 2 PreOuts (2V, Front + Rear/Subwoofer)
- 24-bit DAC
- Front AUX Input (3.5mm mini jack)
- Steering Wheel Remote Control Ready
- -20dB Mute
- Remote Control Ready
- Clock
- Detachable DIN Trim Plate
- Detachable Face Plate
- Dimmer
- Power Antenna Lead
- Remote Turn-On

Max Power Output Ratings

- Max Power Output: 4 x 50W

FM Tuner

- Tuning Range: 87.5 - 108.0 MHz

MW Tuner

- Tuning Range: 531 - 1,602 kHz

LW Tuner

- Tuning Range: 153 - 279 kHz

USB

- USB Requirements: USB 1.1/2.0
- Max. Power Consumption: 500 mA
- File System: FAT 16/32

Sound Tuning

- Subwoofer Level Adjustment: 0 to 15 dB
- Subwoofer Phase Setting: 0° or 180°
- High Pass Filter: Off, 80/100/120 Hz
- Low Pass Filter: Off, 80/100/120 Hz
- Bass Level Control Range: ± 7 dB at 100Hz
- Bass Center Frequency: 60/80/100/120 Hz
- Bass Band Width Adjustment (Q): 4 choices (0.5=wide, 1.0=medium, 1.5=medium, 2=narrow)
- Treble Level Control Range: ± 7 dB at 10 kHz
- Treble Center Frequency: 7.5k/10k/12.5k/15k Hz
- Treble Band Width Adjustment (Q): 2 choices (0.75=wide, 1.25=narrow)
- Mid Level Control Range: ± 7 dB
- Mid Center Frequency: 500/1k/1.5k/2.5k Hz
- Mid Band Width Adjustment (Q): 4 choices (0.75=wide, 1.0=medium, 1.25=medium, 1.5=narrow)

General

- Power Requirement: 12V.DC
- Pre Output Voltage (Before Clipping): 2V / 10k ohms
- Aux In: 1.4V / 10k ohms
- Maximum Mounting Angle: 30°
- Weight: 1.2 kg

Dimensions

- Din Size: 1 DIN
- Chassis Size (W x H x D) mm: 178 x 50 x 177 mm